



AcuMifare S600 is rugged and stylish reader. It can operate in Stand-Alone mode for up to 2000 users and trigger relays or as an external keyboard with AcuSmart card

reader. The AcuMifare S600 reader has a metal finish, making it resistant and anti-vandalism. It can be used as a keyboard reader and/or as a AcuMifare cards reader in Stand-Alone mode for up to 2000 users or connected via the Wiegand 26bit interface.

It has a relay output for electric lock and another for alarm, both with programmable time;

Wiegand 26bit input for an external reader;

Backlight on the keys;

Anti-tamper;

Electrical protection circuits;

Buzzer and green, yellow and red LEDs that show the status;

Fully configurable via keyboard, no need to connect to any type of software.



Frequency	HF - 13,56 MHz
Card Read Range	Up to 6 cm
Communication Interface	Wiegand 26 bits (Input/Output)
Transponder	Numeric keypad and reading cards and tags AcuMifare
User capacity	2000
Connections	Lock Relay, Alarm Relay, Exit Button and External Reader (Wiegand 26bit)
Electrical	
Operating Voltage	12 VDC
Idle Current	<60 mA @ 12 VDC

Environmental	
Index of Protection	IP68
Operating Temp.	-45°C to 60°C
Operating Humidity	10% to 90%
Physical	
Dimension	58 x 120 x 20 mm
Net Weight	450 g
Installation	Internal / External

* Considering power by regulated and stabilized source of 12 VDC, installation in environment without electromagnetic noise and without the presence of metallic surfaces near the reader.

Purchase Code:

500.881: AM-S600 Keypad Reader